

RF FEEDBACK SYSTEMS OF THE J-PARC LINAC

Z. Fang, S. Anami, S. Michizono, S. Yamaguchi, KEK
T. Kobayashi, H. Suzuki, JAEA

Abstract

The RF sources of the J-PARC 181-MeV proton linear accelerator (LINAC) consist of 4 solid-state amplifiers and 20 klystrons [1]. The 24 sets of FPGA-based digital RF feedback (FB) control systems had been developed and applied to the LINAC, and the high-power tests had been performed successfully. The test results show that the variations in the cavity amplitude and phase are less than 0.1% and 0.1° without beam loading, or 0.3% and 0.2° with beam loading.

INTRODUCTION

In each RF source of the J-PARC proton LINAC, the RF fields are controlled by an FPGA-based digital RF feedback system installed in a compact PCI, which consists of the CPU, IO, DSP with FPGA, Mixer & IQ modulator, and RF & CLK boards [2][3][4][5]. The block diagram of the RF feedback control system is shown in Fig. 1. Each klystron drives two cavities. The RF signals from two cavity input power monitor signals (RF input) and two cavity monitor signals (RF tank) are down-converted to 12-MHz IF signals by mixers, and connected to 14-bit ADCs in the FPGA board. In the FPGA board, there are two FPGAs (Xilinx XC2V2000) [6]. FPGA0 is used for the real-time-feedback processing of cavity accelerating fields. FPGA1 is used only for measuring the I and Q components of the cavity input power, and the data is used in the DSP board for cavity tuner control calculation. After real-time-feedback processing in FPGA0, as shown in Fig. 2, the FPGA outputs of the I and Q components are sent to 14-bit DACs, and the outputs of the DACs are connected to the inputs of the IQ modulator, which produces 324-MHz RF signals to drive the RF cavities through the klystron amplifier systems.

In the feedback processing in FPGA0 (Fig. 2), firstly, the I and Q components of the 12-MHz down-converted ADC signals of the cavity fields (RF tank) are produced by sampling them with a 48-MHz clock.




Figure 1: Block diagram of the RF feedback control system.

Subsequently, after the phase rotation with amplitude calibration, the I and Q components of the cavity fields are measured. A selector is used to select which one of the cavity fields—cavity 1 or 2 or an average of these fields—will be applied in the feedback calculation loop. For usual operations, the selector for the average fields of cavities 1 and 2 is adopted. A reference table (REF) is used for feedback setting. A PI controller is used in the feedback loop. Two control parameters, PROPORTION and INTEGRAL, are adjusted through the PLC touch panel [7]. Two feedforward tables, FF_base and FF_beam, independently triggered by the RF and BEAM gates, are provided for the excitation compensation of accelerating fields and beam loading, respectively. Thus, we can obtain a flat-top of the RF pulse of the cavity fields even with beam loading by adjusting the timing of the feedforward compensation, namely, the start time of the BEAM gate pulse signal.




Figure 2: Feedback processing in FPGA0.

IQ OFFSETS OF RF CONTROL SYSTEM

In the experiments of the RF control system with FB OFF, we found that even with the FPGA outputs of the I and Q components set to 0, the IQ modulators in the RF control systems still produced a considerable output power. In order to cancel this undesired output, we added the I and Q offsets to the feedback calculation loop as shown in Fig. 2, and each I and Q offsets for the 24 RF control systems of the J-PARC LINAC had been measured and set accurately, as shown in Fig. 3.




Figure 3: I and Q offsets of the 24 RF control systems.





Figure 4: IQ modulator outputs at SDTL4 with FB OFF.

Fig. 4 shows the experimental results of the IQ modulator outputs at SDTL4 with FB OFF. The experiment data were obtained with constant RF amplitude setting and phase scanning of 360°. It can be observed that with IQ offsetting, the performance of the IQ modulator outputs


with FB OFF is improved significantly: 1) almost no output power is delivered when I and Q are set to 0; 2) with phase scanning, the amplitude of the IQ modulator outputs vary by less than 1%.

FEEDBACK PERFORMANCE

High-power tests were performed for the 24 RF systems of the J-PARC LINAC. Fig. 5 shows an example of the cavity outputs with FB ON at SDTL7 with full power operation. The RF amplitude is set to 4000 and the phase is set to 0°. From Fig. 5, it can be observed that the variation in the cavity amplitude in the flat-top is less than 0.1%. Also the test results show that the variation in the cavity phase is less than 0.1°.



a) full scale of cavity and DAC amplitude waveform.



b) expansion of flat top of cavity amplitude.

Figure 5: Amplitudes of cavity and DAC outputs with FB ON at SDTL7.

FEEDBACK WITH BEAM LOADING COMPENSATION

The J-PARC 181-MeV proton LINAC was commissioned in October 2006, and a proton beam was successfully accelerated to 181 MeV on January 24, 2007. After beam study, a proton beam with a peak current of 26 mA and a pulse width of 50 μ s was successfully achieved in May 2007. In order to obtain a flat-top for the cavity accelerating fields even with beam loading, a beam feedforward table for the compensation of the beam loading was added to the feedback loop of the RF feedback control

system corresponding to the beam pulse ranging from 200 to 250 μs . Fig. 6 shows an example of the cavity fields at SDTL3 with the loading beam of 26 mA and 50 μs . It shows that in the case of beam loading, the variations in the amplitude and phase of the cavity fields are successfully maintained within 0.3% and 0.2° , respectively, by means of beam feedforward compensation.




Figure 6: Amplitudes of cavity and DAC outputs at SDTL3 with beam feedforward compensation.


STABILITY OF RF FEEDBACK SYSTEM

The stability of the RF feedback system during a long-duration operation was measured through an external monitor [8]. Fig. 7 shows an example of the test results at DTL3. From this figure, it can be observed that during the 48-hour operation from May 21–23, 2007, the peak-to-peak amplitude error in the pulse is approximately 0.1% without beam loading or 0.3% with beam loading. The absolute drift of the amplitude is maintained within approximately 0.2%. The peak-to-peak phase error in the pulse is approximately 0.1° without beam loading or 0.2° with beam loading. Almost no absolute drift of the phase is observed.


SUMMARY

The 24 sets of FPGA-based RF feedback control systems had been developed and applied to the J-PARC 181-MeV proton LINAC, and the high-power tests had been performed successfully. In case of FB OFF, the amplitude of the RF systems varies less than 1% with a phase scanning of 360° . For FB ON, the variations in the cavity amplitude and phase are less than 0.1% and 0.1° without beam loading, or 0.3% and 0.2° with beam loading, respectively. Moreover, the RF feedback systems exhibited a considerably high stability for a long-duration operation.

Basing on the developed RF feedback systems mentioned above, a proton beam of 181 MeV with a peak current of 26 mA and a pulse width of 50 μs was successfully achieved in May 2007. Further beam study for a peak current of 50 mA and a pulse width of 500 μs will be continued in the coming months by adjusting the beam loading compensation in the RF feedback control systems.



a) amplitude.



b) phase.

Figure 7: Stability of the RF feedback control system at DTL3.

REFERENCES

- [1] T. Kobayashi et al., "Performance of J-PARC Linac RF System", this conference.
- [2] S. Anami et al., "Control of the Low Level RF System for the J-PARC Linac", LINAC 2004, 739–741, Germany.
- [3] S. Michizono et al., "Digital Feedback System for J-PARC Linac RF Source", LINAC 2004, 742–744, Germany.
- [4] S. Anami et al., "J-PARC Linac Low Level RF Control", Proceedings of the 1st Japan Particle Accelerator Conference and the 29th Linear Accelerator Meeting in Japan, 2004.
- [5] S. Michizono et al., "Digital LLRF Feedback Control System for the J-PARC Linac", Proceedings of the 2nd Japan Particle Accelerator Conference and the 30th Linear Accelerator Meeting in Japan, 2005.
- [6] Z. Fang et al., "Stabilization of Accelerating Field Using FPGA for J-PARC Linac", Proceedings of the 3rd Japan Particle Accelerator Conference and the 31st Linear Accelerator Meeting in Japan, 2006.
- [7] H. Suzuki et al., "PLC control of J-PARC LowLevel RF System", this conference.
- [8] S. Michizono et al., "Performance of Digital LLRF Field Control System for the J-PARC Linac", LINAC 2006, USA.